

purolinear 360™

how to order

Specify your Purolinear 360 system by building your item numbers using the tables below, selecting from left to right the desired option from each column. Purolinear 360 can be ordered two ways: either as components by specifying your desired number of Luminaires, Connectors, and Drivers, or by using the Preconfigured Quick Spec table to customize one of the options shown on the opposite page.

SYSTEM ORDERING

Luminaire Ordering Table

Family	Category	Finish	Length	CCT	CRI
23 Purolinear 360	L Luminaire	PC Polished Chrome	24 24"	30 3000K	90 Min. 90
		SC Satin Chrome	36 36"		
		SK Satin Black	48 48"		
		SW Satin White			

Example Luminaire Item Number:

2 3 L S K 2 4 3 0 9 0

Connector Ordering Table

Family	Category	Finish	Style	Canopy	Electrical Type
23 Purolinear 360	C Connector	PC Polished Chrome	E1 Small End Connector	0 No 1 Yes ¹	1 Live
		SC Satin Chrome	E2 Large End Connector		
		SK Satin Black	L1 Small Linear Connector		
		SW Satin White	L2 Large Linear Connector		
			C2 Large Corner Connector		
			T2 Large T Connector		
	X2 Large X Connector				

Example Connector Item Number:

2 3 C S K E 1 0 1

Driver Ordering Table

Family	Category	Driver Location	Total Luminaire Length ⁴	Driver Input Voltage	Driver Dimming
23 Purolinear 360	D Driver	B Outlet Box ²	08 Up to 8'	120 120V	PHA Phase (Triac/ELV)
		R Remote	12 Up to 12'	230 230V	010 0-10V
		S Switch ³	20 Up to 20'	277 277V	SWT Built-in switch ⁵
			32 Up to 32'		

Example Driver Item Number:

2 3 D B 0 3 1 2 0 P H A

PRECONFIGURED QUICK SPEC ORDERING

Family	Category	Finish	Style	Length A	Length B	Driver Location	Driver Input Voltage	Driver Dimming
23 Purolinear 360	Q Quick Spec	PC Polished Chrome	L1 Single Linear ⁶	2 2'	0 N/A	B Outlet Box ⁷	120 120V	PHA Phase (Triac/ELV)
		SC Satin Chrome	L2 Double Linear	3 3'	2 2'	R Remote	230 230V	010 0-10V
		SK Satin Black	N1 Single N	4 4'	3 3'	S Switch ³	277 277V	SWT Built-in switch ⁵
		SW Satin White	N2 Double N		4 4'			
			SR Square/Rectangle					

Example Quick Spec Item Number:

2 3 Q S K L 1 2 0 B 1 2 0 P H A

¹ Only available for E1 and L1 Connector Styles

² Driver can be installed in a standard 4" octagon box. Only available for Total Luminaire Length 08. Requires a connector with a canopy.

³ Requires use of our provided wall dimmer switch with built-in LED driver on a dedicated circuit; must specify Driver Input Voltage 120 and Driver Dimming SWT

⁴ For Total Luminaire Lengths greater than 32, split configuration into two or more circuits and specify a driver for each circuit. Refer to the assembly instructions for how to electrically isolate different sections of a configuration.

⁵ Must specify Driver Location S

⁶ Must specify Length B 0

⁷ Driver can be installed in a standard 4" octagon box. Only available for Style L1 and L2. Selecting Driver Location B for Style L2 gives a center-mounted canopy.